

#### X66C6 / X66C6S

#### Features:

- Excitation system: self-excited (AREP and PMG are optional)
- ATS (automatic transfer switch) receptacle
- Lockable battery isolator switch
- Stainless galvanized zinc plates with strong corrosion resistance
- Vibration isolators between the engine/alternator and base frame
- Integrated wiring design
- Base fuel tank for at least 8 hours running
- Equipped with an industrial muffler
- Engine oil pump
- 50 ℃ radiator
- Top lifting and steel base frame with forklift holes
- Drainage for fuel tank
- Complete protection functions and safety labels
- IP54 (soundproof sets), IP56 (control system)
- Water jacket preheater, oil heater and double air cleaner, etc. are available.

	古	630
		equis power
	DE Consulta pourse	
0		
		1 innuar
		equispower

Output Ratings		
Generating Set Model	Prime	Standby
X66C6/S	73kVA/58kW	80kVA/64kW

Ratings at 0.8 power factor.

Ratings and Performance Data				
Engine Make & Model:		4BTA3.9-G2		
Alternator Mode	UCI224E			
Alternator Brand:		STAMFORD		
Control System:		PLC-920 / PLC-7420		
Noise Level@7m:		62.4		
Frequency & Phase:		60Hz & 3PH		
Engine Speed: R	PM	1800		
Structure Type:	X66C6	Α		
ou dotalo Typol	X66C6S	R		
Fuel Tank Capacity: L	X66C6	226		
r der rank Sapacity. E	X66C6S	360		
Fuel Consumption: I/hr	Prime	9.3		
(100% Load)	Standby	10.3		


Also available in the following voltages: 415/240V-380/220V-220/127V-200/115V;


ESP: Standby Power Standby duty, operation under variable load, without over load;


PRP: Prime Power-Continuous duty operation, under variable load 24/24h-10% over load permissible 1 hour/12 hours; The data is only for your reference but not for use of sales.

M: Mechanical speed governor, E/ECU: Electronic speed governor;

NA: Naturally aspirated, TC: Turbocharged, TCA: Turbocharged and air-air aftercooled. TCW: Water-cooled Turbocharged; The weights are approximate and without fuel











# X66C6 / X66C6S

### Engine model: 4BTA3.9-G2

The test on the date				
Typical engine data  Net weight	kg	321		
Rotate part instantaneous inertia _ without flywheel	kg.m2	0.143		
Distance between gravity center and rear surface of cylinder block	mm	373		
Distance between gravity center and center line above of crankshaft	mm	163		
Engine installation				
Static bent torque permitted—rear surface of cylinder block	N.m	1356		
Static bent torque permitted—front surface of cylinder block	N.m	435		
Static bent torque permitted—flank surface of cylinder block	N.m	365		
Exhaust system				
Max. back pressure	mmHg	76		
Diameter of exhaust pipe recommended	mm	75		
Air intake system				
Max. air intake resistance				
Dirty filter	mmH2O	635		
Normal air cleaner and clean filter	mmH2O	254		
Heavy duty cleaner and clean filter	mmH2O	381		
Diameter of intake pipe recommended	mm	75		
Lubrication system				
Normal oil pressure range				
Low idle	kPa	207		
Rated speed	kPa	345		
Max. oil temperature permitted in oil pan	℃	121		
Oil pan capacity (Max _ Min)	L	9.5_8.5		
Lubrication system Min. capacity (oil pan + oil filter) Usage inclining degree permitted (any direction)	L °	10.9 40		
		40		
Fuel system Fuel injection pump model	BYC A pump with GAC governor			
Max. fuel input resistance of transfer pump	mmHg	102		
Max. overflow fuel resistance at overflow pipe of injector	mmHg	254		
Total fuel overflow amount	L/h	30		
Cooling avatam				
Cooling system Coolant capacity-engine only	L	7.2		
Max. coolant cycling resistance exterior engine	kPa	28		
Thermostat adjusting temperature (range)	$^{\circ}\mathbb{C}$	82 95		
Min. opening pressure of radiator cap	kPa	<u>-</u> 69		
Max. coolant temperature permitted _ Standby Power/Base output Power	$^{\circ}$ C	104/100		
Electric system				
Starter	12V	24V		
Battery charging system	63A	40A		
Max. starting circuit resistance	$0.00075\Omega$	0.002Ω		
Min. battery capacity12℃ (CCA: Cold Cranking Ampere)	625CCA	312CCA		
Technical data _ under standard fuel delivery rate FR L003	Base output Power	Standby Power		
Engine speed _ RPM	1500	1500		
Output Power _ kW	36	40		
Torque _ Nm	229	255		
Low idle _ RPM	950-1050	950-1050		
Friction energy output _ kW	8.2	8.2		
Piston speed _ m/s	6.0	6.0		
Engine coolant flow _ L/sec	2.2	2.2		
Air intake flow _ L/sec	43.6	44.9		
Exhaust flow _ L/sec	101	108		
Exhaust temperature _ °C	463	487		
Environment energy output _ kW	N/A	N/A		
Coolant energy output _ kW	25.9	29		
Fuel energy output _ kW	N/A	N/A		



# X66C6 / X66C6S

#### Alternator model: UCI224E

CONTROL SYSTEM	SEPARATELY EXCITED BY P.M.G.							
A.V.R.	MX321	MX341						
VOLTAGE REGULATION	± 0.5 %	± 1.0 %	With 4% FN	GINE GOVE	RNING			
SUSTAINED SHORT CIRCUIT	± 0.5 %							
edentitle energi			220		c (page . )	<u> </u>		
CONTROL SYSTEM	SELF EXCITED							
A.V.R.	SX460 AS440							
VOLTAGE REGULATION	± 1.0 %	± 1.0 %	1.0 % With 4% ENGINE GOVERNING					
SUSTAINED SHORT CIRCUIT	SERIES 4 CONTROL DOES NOT SUSTAIN A SHORT CIRCUIT CURRENT							
INSULATION SYSTEM	CLASS H							
PROTECTION	IP23							
RATED POWER FACTOR	0.8							
STATOR WINDING	DOUBLE LAYER CONCENTRIC							
WINDING PITCH	TWO THIRDS							
WINDING LEADS	12							
STATOR WDG. RESISTANCE	0.101 Ohms PER PHASE AT 22°C SERIES STAR CONNECTED							
ROTOR WDG. RESISTANCE		0.101 0	TIIIIST LICTT			TAIL OOMINE	OTED	
	0.69 Ohms at 22°C 20 Ohms at 22°C							
EXCITER STATOR RESISTANCE			0.070		PHASE AT 2	2000		
EXCITER ROTOR RESISTANCE	50 511							
R.F.I. SUPPRESSION	BS EN 61000-6-2 & BS EN 61000-6-4,VDE 0875G, VDE 0875N. refer to factory for others							
WAVEFORM DISTORTION	NO LOAD < 1.5% NON-DISTORTING BALANCED LINEAR LOAD < 5.0%							
MAXIMUM OVERSPEED				2250 R				
BEARING DRIVE END				BALL. 6312	. ,			
BEARING NON-DRIVE END	BALL. 6309-2RS (ISO)							
INFIGUE COMP. CENERATOR			ARING		2 BEARING			
WEIGHT COMP. GENERATOR WEIGHT WOUND STATOR			1 kg 3 kg		330 kg 103 kg			
WEIGHT WOUND ROTOR			89 kg		87.52 kg			
WR <sup>2</sup> INERTIA			9 kgm²		0.4682 kgm <sup>2</sup>			
SHIPPING WEIGHTS in a crate			1 kg		351 kg			
PACKING CRATE SIZE		105 x 57	x 96(cm)		105 x 57 x 96(cm)			
			Hz			60		
TELEPHONE INTERFERENCE			<2%		TIF<50			
COOLING AIR	000/000		ec 458 cfm	440/054	440/040	0.281 m³/se		400/077
VOLTAGE SERIES STAR VOLTAGE PARALLEL STAR	380/220	400/231	415/240	440/254	416/240	440/254	460/266	480/277 240/138
VOLTAGE PARALLEL STAR  VOLTAGE SERIES DELTA	190/110 220/110	200/115	208/120 240/120	220/127 254/127	208/120 240/120	220/127 254/127	230/133 266/133	277/138
KVA BASE RATING FOR REACTANCE	60	60	60	45	67.5	70	72.5	75
VALUES  Xd DIR. AXIS SYNCHRONOUS	2.48	2.24	2.08	1.39	3.00	2.78	2.64	2.50
X'd DIR. AXIS TRANSIENT	0.19	0.17	0.16	0.11	0.22	0.20	0.19	0.18
X"d DIR. AXIS SUBTRANSIENT	0.13	0.17	0.10	0.11	0.22	0.20	0.19	0.13
Xq QUAD. AXIS REACTANCE	1.13	1.02	0.95	0.63	1.38	1.28	1.21	1.15
X"q QUAD. AXIS SUBTRANSIENT	0.14	0.13	0.12	0.08	0.14	0.13	0.12	0.12
XL LEAKAGE REACTANCE	0.08	0.08	0.07	0.05	0.09	0.08	0.08	0.08
X <sub>2</sub> NEGATIVE SEQUENCE	0.13	0.12	0.11	0.07	0.14	0.13	0.12	0.12
X <sub>0</sub> ZERO SEQUENCE	0.11	0.10	0.09	0.06	0.09	0.08	0.08	0.08
REACTANCES ARE SATURAT	ED	V	ALUES ARE			ND VOLTAGI	INDICATE	D
T'd TRANSIENT TIME CONST.				0.02				
T''d SUB-TRANSTIME CONST. T'do O.C. FIELD TIME CONST.	0.007 s 0.7 s							
Ta ARMATURE TIME CONST.	0.006 s							
SHORT CIRCUIT RATIO								